

```

// C Code to initialize the AC Relay Wildcard

#include <allqed.h>                // Include QED header files
#define RELAY_CONTROL_LINES        1
#define DIRECTION_REGISTER         0xC005
#define RELAY_CONTROL_REGISTER    0xC000
#define ALL_RELAYS                 0xF

void Init_AC_Relay ( uchar module_number ) // Valid module numbers are
0-7
// Initializes the AC Relay Wildcard by configuring the AC relay
control lines
// of the CPLD to outputs.  The module number depends on the module
select
// jumpers.  See Table 1 for the jumper settings and associated
addresses.
{
    EXTENDED_ADDR module_addr;

    module_addr.page16 = module_number;
    module_addr.addr16 = RELAY_CONTROL_REGISTER;

    // Turn all relays off before initializing control lines to outputs.
    // Relays are active low (i.e. writing a 0 to the relay turns it on).
    StoreChar( ALL_RELAYS, module_addr.addr32 );

    module_addr.addr16 = DIRECTION_REGISTER;

    StoreChar( RELAY_CONTROL_LINES, module_addr.addr32);
}

```