



**Summary**

The following explains how to accommodate a manufacturer's slow display using the QED Board.

**Description**

Some manufacturer's displays operate more slowly than they are spec-ed. To accomodate these displays using the QED Board, the following bytes in the QED-Forth v2.01 PROM should be reprogrammed (Numbers are in Hex):

| <b>Location:</b> | <b>Should be:</b> | <b>Was:</b> |
|------------------|-------------------|-------------|
| 487F             | 5C                | 32          |
| 4906             | 0D                | 06          |
| 4907             | 48                | A4          |
| 4941             | 20                | 10          |
| 4942             | 08                | 04          |

If you have any questions please contact Melody Liu at 510/790-1255.

The information provided herein is believed to be reliable; however, Mosaic Industries assumes no responsibility for inaccuracies or omissions. Mosaic Industries assumes no responsibility for the use of this information and all use of such information shall be entirely at the user's own risk.